

DMX-X02

DMX Live And Stand Alone Controller



Summary

DMX-X02 is a full-color LED DMX control system which focuses on indoor and outdoor decorative lighting, which can be used stand alone or with computer. It comprises scene-edit software. You can edit various lighting effects by downloading the programme which edit according to your special requirement from your PC. This control system can fulfill 256 grey levels for each R,G,B color, totally 16.77 million real full-color. The software has been developed specially for architectural lighting and features easy to use effects which can be dropped onto timelines, along with multi-zone and synchronization allowing you to program a project with multiple rooms and areas with ease


Product Features

- Meets DMX512/1990
- 512 DMX Channels PC or Stand Alone
- USB 2.0 connection program by software
- Various Output Interface, XLR-3 / RJ45 / Green terminal
- SD card of internal memory
- Default scene triggering when power up
- Stand Alone Memory capacity:5000 steps to 100 steps
- Compatible with any DMX fixture and DMX LED driver
- Euchips X-DMX software compatible

Technical Parameters

Input Voltage :	5V DC, 0.15A-1A (by USB)
Power Consumption :	< 2W
Connection :	USB 2.0
Output connector :	XLR3, RJ45, Green Terminal
Transmission signal :	DMX512 (1990)
Output channels :	512 DMX channels
Stand Alone mode :	512 DMX channels
Lamp type :	Wallwashing light, Tube light, Cube light, etc.
OS Requirement :	Windows XP/Vista/Seven/Win10 32/64 1Ghz CPU, 512 MB RAM
PC Software :	Euchips X-DMX
Environment :	IP20, -25 C to 70 C


Interface Introduction



- M+ :MODE+
- M- :MODE-
- Brightness :4 level brightness
- White :switch between RGB and white
- ON/OFF : turn on/turn off light


Live Use With Computer

**DMX OUT
512DMX Channels**




Stand Alone Use

**DMX OUT
512DMX Channels**



Recommended DMX512 Installation



Software

EuchipsX-DMX has evolved over the years for architectural lighting control. It only requires a few minutes to setup the software and gain full control of any kind of lighting.

